



30 Amp to 50 Amp RV Surge Protector Adapter with Indicator, NEMA TT-30P to NEMA 14-50R

Plug and Connector Type: NEMA TT-30P Male to NEMA 14-50R Female

This is the 30 to 50 amp RV surge adapter with the indicator fittings: LED status lights on the housing and a weather cover over the NEMA 14-50R socket. The plug and socket are the same as the plain 30 amp to 50 amp adapter, so it steps a 50 amp coach cord down to a 30 amp pedestal in the same way. Rated 30A 125V on the plug side and built to UL 817 with UL and cULus listing. The cover keeps rain and grit out of the receptacle between hookups, which matters at sites where the pedestal faces the weather.

E-mail Now

RV Surge Protector Adapters

Specifications

Label	Value
Product Name:	30 Amp to 50 Amp RV Surge Protector Adapter with Indicator, NEMA TT-30P to NEMA 14-50R
Adapter Type:	NEMA TT-30P Male Plug to NEMA 14-50R Female Receptacle
Male Plug Connector:	NEMA TT-30P
Female Receptacle Connector:	NEMA 14-50R
Male Plug Current Rating:	30A
Female Receptacle Current Rating:	50A
Maximum Current:	50A
Voltage Rating:	125V/250V
Prong Configuration:	3 prong 2 poles 3 wires (male plug) / 4 prong 3 poles 4 wires (female receptacle)
Power Indicator:	LED power indicator fitted at the plug end
Standard:	UL 817
Safety Approvals:	UL, cULus
Environmental Certifications:	RoHS, REACH
Housing Material:	PA66 Flame-Retardant Engineering Plastic
Contact / Blade Material:	Nickel-Coated Brass, Pure Copper Conductive Parts
Flammability Rating:	UL 94 V-0
Temperature Rating:	-40 C to +75 C
Color:	Black is standard; any color available on request
Testing:	Hi-Pot (Dielectric Withstand), Polarity (Pinout) and Continuity
Customization:	OEM / ODM; custom colors, packaging and labeling available
Country of Origin:	Made in China
Packing:	Standard Export Carton

Typical Applications

Pick this version when the adapter stays plugged in for weeks at a time: the indicator gives you a status read at a glance, and the cover protects the socket face when the coach cord is unplugged. Same 30 to 50 amp job as the 30 amp to 50 amp adapter, same limits: 125V, up to 30A.

Before You Plug In

Read the indicator after the first hookup, not after something stops working. It reports the state of the supply you are plugged into, so a fault at the pedestal shows up before it reaches the coach.

Ordering Notes

Indicator and cover are the only differences from the 30 amp to 50 amp adapter. Specify the indicator version if you need those fittings.

Our other certificated products



Yuyao ChengBang

Tel: 0086-574-62160227 Fax: 0086-574-62615227

E-mail: sales@chinapowercords.com <https://www.chinapowercords.com>

Simen Town, Yuyao

Ningbo / Zhejiang, China
315400