



30 Amp RV Surge Protector Adapter with Indicator, NEMA L14-30P to NEMA TT-30R

Plug and Connector Type: NEMA L14-30P Male to NEMA TT-30R Female

This is the NEMA L14-30P to NEMA TT-30R adapter with the indicator and cover fitted, matching the plain build in ratings and wiring.

Home hookups are usually left connected for days, and the cover protects the RV socket when the trailer is unplugged. The LED panel reports the state of the outlet the adapter sits on.

E-mail Now

RV Surge Protector Adapters

Specifications

Label	Value
Product Name:	30 Amp RV Surge Protector Adapter with Indicator, NEMA L14-30P to NEMA TT-30R
Adapter Type:	NEMA L14-30P Male Plug to NEMA TT-30R Female Receptacle
Male Plug Connector:	NEMA L14-30P
Female Receptacle Connector:	NEMA TT-30R
Male Plug Current Rating:	30A
Female Receptacle Current Rating:	30A
Maximum Current:	30A
Voltage Rating:	125V/250V
Prong Configuration:	4 prong 3 poles 4 wires (male plug) / 3 prong 2 poles 3 wires (female receptacle)
Power Indicator:	LED power indicator fitted at the plug end
Standard:	UL 817
Safety Approvals:	UL, cULus
Environmental Certifications:	RoHS, REACH
Housing Material:	PA66 Flame-Retardant Engineering Plastic
Contact / Blade Material:	Nickel-Coated Brass, Pure Copper Conductive Parts
Flammability Rating:	UL 94 V-0
Temperature Rating:	-40 C to +75 C
Color:	Black is standard; any color available on request
Testing:	Hi-Pot (Dielectric Withstand), Polarity (Pinout) and Continuity
Customization:	OEM / ODM; custom colors, packaging and labeling available
Country of Origin:	Made in China
Packing:	Standard Export Carton

Typical Applications

Trailers parked at home on an L14-30 outlet, standby generator feeds, and shop connections made often enough to want a status read each time. Trailer side stays 30A 125V.

Before You Plug In

Check the indicator after each hookup rather than leaving it to chance, and have the outlet wiring verified before the season starts.

Ordering Notes

Order the indicator version when both are required. The plain build is the same part without those fittings.

Our other certificated products



Yuyao ChengBang

Tel: 0086-574-62160227 Fax: 0086-574-62615227

E-mail: sales@chinapowercords.com <https://www.chinapowercords.com>

Simen Town, Yuyao
Ningbo / Zhejiang, China
315400