



30 Amp RV Surge Protector Adapter with Indicator, NEMA L5-30P to NEMA TT-30R

Plug and Connector Type: NEMA L5-30P Male to NEMA TT-30R Female

The NEMA L5-30P to NEMA TT-30R adapter with the indicator puts the indicator and weather cover on the NEMA L5-30P to NEMA TT-30R adapter. The connection is the same as the NEMA L5-30P to NEMA TT-30R adapter, 30A 125V, UL 817 with UL and cULus listing.

It suits connections that are left in place: the cover keeps the RV socket clean between stays, and the LED panel reports the state of the locking outlet the adapter is plugged into.

E-mail Now

RV Surge Protector Adapters

Specifications

Label	Value
Product Name:	30 Amp RV Surge Protector Adapter with Indicator, NEMA L5-30P to NEMA TT-30R
Adapter Type:	NEMA L5-30P Male Plug to NEMA TT-30R Female Receptacle
Male Plug Connector:	NEMA L5-30P
Female Receptacle Connector:	NEMA TT-30R
Male Plug Current Rating:	30A
Female Receptacle Current Rating:	30A
Maximum Current:	30A
Voltage Rating:	125V
Prong Configuration:	3 prong 2 poles 3 wires
Power Indicator:	LED power indicator fitted at the plug end
Standard:	UL 817
Safety Approvals:	UL, cULus
Environmental Certifications:	RoHS, REACH
Housing Material:	PA66 Flame-Retardant Engineering Plastic
Contact / Blade Material:	Nickel-Coated Brass, Pure Copper Conductive Parts
Flammability Rating:	UL 94 V-0
Temperature Rating:	-40 C to +75 C
Color:	Black is standard; any color available on request
Testing:	Hi-Pot (Dielectric Withstand), Polarity (Pinout) and Continuity
Customization:	OEM / ODM; custom colors, packaging and labeling available
Country of Origin:	Made in China
Packing:	Standard Export Carton

Typical Applications

Dock and yard hookups where the adapter is part of the permanent setup, and for trailers that are connected and disconnected around a boat or a work truck. Current and voltage do not change from the plain version.

Before You Plug In

Read the indicator on first hookup each season, then check the trailer cord end for heat marks. If the supply shows a fault, fix the outlet rather than compensating somewhere else in the chain.

Ordering Notes

Order the indicator version when both are required. The plain build is the same part without them.

Our other certificated products



Yuyao ChengBang

Tel: 0086-574-62160227 Fax: 0086-574-62615227

E-mail: sales@chinapowercords.com <https://www.chinapowercords.com>

Simen Town, Yuyao
Ningbo / Zhejiang, China
315400