



50 Amp to 30 Amp RV Surge Protector Adapter with Indicator, NEMA 14-50P to NEMA TT-30R

Plug and Connector Type: NEMA 14-50P Male to NEMA TT-30R Female

This is the 50 to 30 amp RV adapter with the indicator and cover fitted. Same job as the 50 amp to 30 amp adapter: NEMA 14-50P plug at the pedestal, NEMA TT-30R socket for the trailer cord.

The difference is at the housing. The LED panel shows the state of the supply, and the cover closes over the receptacle when the trailer is unplugged. Both are worth having on a part that spends the season outdoors.

E-mail Now

RV Surge Protector Adapters

Specifications

Label	Value
Product Name:	50 Amp to 30 Amp RV Surge Protector Adapter with Indicator, NEMA 14-50P to NEMA TT-30R
Adapter Type:	NEMA 14-50P Male Plug to NEMA TT-30R Female Receptacle
Male Plug Connector:	NEMA 14-50P
Female Receptacle Connector:	NEMA TT-30R
Male Plug Current Rating:	50A
Female Receptacle Current Rating:	30A
Maximum Current:	50A
Voltage Rating:	125V/250V
Prong Configuration:	4 prong 3 poles 4 wires (male plug) / 3 prong 2 poles 3 wires (female receptacle)
Power Indicator:	LED power indicator fitted at the plug end
Standard:	UL 817
Safety Approvals:	UL, cULus
Environmental Certifications:	RoHS, REACH
Housing Material:	PA66 Flame-Retardant Engineering Plastic
Contact / Blade Material:	Nickel-Coated Brass, Pure Copper Conductive Parts
Flammability Rating:	UL 94 V-0
Temperature Rating:	-40 C to +75 C
Color:	Black is standard; any color available on request
Testing:	Hi-Pot (Dielectric Withstand), Polarity (Pinout) and Continuity
Customization:	OEM / ODM; custom colors, packaging and labeling available
Country of Origin:	Made in China
Packing:	Standard Export Carton

Typical Applications

For a 30 amp trailer that is regularly parked on 50 amp sites, and for anyone who wants to see at a glance that the pedestal is sound before the coach is connected. Ratings do not change from the 50 amp to 30 amp adapter: the trailer side stays 30A 125V.

Before You Plug In

If the indicator shows a fault, do not work around it with another adapter. Move to a different pedestal or report it to the park office, then check the trailer cord end at the same time.

Ordering Notes

Order the indicator version when both are required. The plain 50 amp to 30 amp adapter is the same adapter without those fittings.

Our other certificated products



Yuyao ChengBang

Tel: 0086-574-62160227 Fax: 0086-574-62615227

E-mail: sales@chinapowercords.com <https://www.chinapowercords.com>

Simen Town, Yuyao

Ningbo / Zhejiang, China
315400